

SPECIFICATION		ELECTRIC BOOSTER PUMPS				ELECTRIC WATER PUMPS			
		EBP15	EBP23	EBP25	EBP40	EWP80	EWP115	EWP130	EWP150
Flow Rate (Max)	L/Min	15	23	25	37	80	115	130	150
	Gal/Min	4	6.1	6.6	9.8	21.1	30.4	34.3	39.6
Pump Material	Nylon 66	Yes	Yes	Yes	Yes	Yes	Yes	No	No
	Alloy	No	No	No	No	No	Yes	Yes	Yes
Voltage	12 Volt	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
	24 Volt	No	No	No	Yes	No	Yes	Yes	Yes
Operating Temp	C	-40 to 120	-40 to 120	-40 to 120	-40 to 120	-20 to 130	-40 to 130	-40 to 130	-40 to 130
	F	-4 to 248	-4 to 248	-4 to 248	-4 to 248	-4 to 248	-4 to 248	-4 to 248	-4 to 248
Weight	Grams	245	364	995	570	900	923	1,107	1,170
	Pounds	0.54	0.8	2.19	1.25	2.0	2.16	2.6	2.6
Fits Hose Size		12.5 to 19mm	12.5 to 19mm	19mm	19mm	32 to 51mm	38 to 51mm	32 to 51mm	38 to 51mm
Engine Size (Litres)		Motorbikes, Heater Systems & Solar				up to 2	2 - 3.5	3.5 - 5	5+

## Product Selection Guide Electric Water Pumps & Controllers

Application	Pump Model	Pump Kit		Pump Combo		Controller / Switch	
		Part # 12 V	Part # 24 V	Part # 12 V	Part # 24 V	Part # 12 V	Part # 24 V
Motorbike up to 500cc (Standard)	EBP*15	9001				0444 or 0455	
Motorbike 500cc - 1000cc (Std)	EBP*23	9050				0444 or 0455	
Motorbike 1000cc - 2000cc (Std)	EBP*25	9005				0444 or 0455	
Vehicle Heater System (Standard)	EBP*23	9050				0444 or 0455	
LPG (Butane) System (Standard)	EBP*23	9050				0444 or 0455	
Intercooler (depending on capacity)	EBP*23	9050					
	EBP*25	9005					
	EBP*40	9040	9041			0444 or 0455	0444 or 0455
	EWP*80	8005		8907			
Engines up to 2.0L (Standard)	EWP*80	8005		8907		8001	8001
Engines up to 2.0L - 3.5L (Standard)	EWP*115	8025 or 8040	8026 or 8041	8930 or 8950	8931 or 8951	8001	8001
Engines up to 3.5L - 5.0L (Standard)	EWP*130	8080	8081	8990	8991	8001	8001
Engines 5.0L or greater (Standard)	EWP*150	8060	8061	8970	8971	8001	8001
Modified Engines Supercharged/Turbo	EWP*150	8060	8061	8970	8971	8001	8001
Drag Racing, Drifting & Speedway	EWP*150	8060	8061	8970	8971	8001	8001
Off Road / 4WDs	EWP*130	8080	8081	8990	8991	8001	8001
Solar Hot Water Systems (depending on size)	EBP*15	9001				0444 or 0455	
	EBP*23	9050				0444 or 0455	
	EBP*25	9005				0444 or 0455	
	EBP*40	9040	9041			0444 or 0455	0444 or 0455