

JEGS Classic 630 Series Stereo Radio Specs.

Radio Specifications

FM Section

Frequency Range87.5-108 MHz
Usable Sensitivity ...9dBf (0.8 μ V/75 Ω mono,
.....S/N 36dB)
Signal-to-noise ratio72 dB

IF Frequency10.7MHz
S/N Ratio60dB
Capture Ratio1.5dB
Separation35dB

AM Section

Frequency Range530-1710KHz
S/N Ratio62dB
Usable Sensitivity25

Audio Section

Output Channel45w RMS X4
Output Impedance4-8 ohm per speaker
Response30Hz-18KHz

Maximum Power .. (4x75) 300w Peak
THD5%

USB

File compatibility.....MP3/WMA

General

Power Supply12VDC Negative Ground
Speaker impedance4-8 ohm
Stand-By Current0.02A
Fuse Memory (bat)10 amp
Fuse Accesory (ign)1 amp
Chassis 200mm(7-3/4")(w) x 50mm(2") (H)
x150mm (5-7/8")(D)